One Hub For All Your Needs



SPECIFICATIONS

Features	Descriptions
Battery	
Battery Chemistry	NMC
Capacity	1554Wh
Lifecycle	>800 cycles to 60%
Battery Management	BMS : Under/Over Voltage Protection, Over Current Protection, Short Circuit Protection, Overcharging Voltage Protection, Over Temperature Protection
MPPT	Support solar power MPPT charging
Input Options	
Solar Charge	2.5Hrs (Maximum Input under full sunlight), 800W (15-100V, 12A)
Vehicle Charge	12Hrs (at 12V)12V, 12A
Wall Charge	1Hour to 80%, 1.6Hours to 100%, up to 1500W
Output	
AC Outlets	4 x 110Vac, 60Hz, 2000W (4000W Peak)
Car Outlet	13.6V, 10A
USB-A	2 x 12W Max (5V, 2.4A)
Quick Charge 3.0	2 x 28W Max (5V/9V/12V, 2.4A)
USB-C PD	2 x 60W Max (5V/9V/15V/20V, 3A)
Wireless Charging	1 x 15W Max
Advanced	
UPS	Yes
Battery Expansion	Parallel to increase capacity (Up to 3 Units)
App Management	Yes (Wi-Fi +Bluetooth)
General	
Dimensions (LxWxH)	16.5 x 9.1 x 11.3 in (418.7 x 230 x 287mm)
Weight	⁻ 36.4lbs (16.5kg)
Operating Temperature	-4 ~ 140°F (-20~60°C)
Certifications	UL, CE, FCC, RoHS, PSE
Warranty	24 Months

SHENZHEN GROWATT NEW ENERGY CO., LTD

12/F, Building A, Sino-German(Europe) Industrial Park, Hangcheng Ave, Guxing Community, Xixiang Subdistrict, Bao'an District, Shenzhen, China W: www.growattportable.com E: marketing.pps@growatt.com **INFINITY 1500**



2000W AC output for high power device:







12 Outlets for all kinds of electric devices



1.6Hrs superfast charging speed



UPS seamless power switch in power outages



supports remote monitoring & control

Your EXPERT **Portable Power Station**

Power Wherever You Need

Powerful Capacity & Output

With a huge capacity of 1554Wh and a powerful output of 2000W, you can now power a wider array of high-power appliances with confidence!



The Most Versatile Ports

With up to 12 versatile outlets, you may charge all of your devices simultaneously without cumbersome wiring and confusing adapters.






INFINITY 1500 has the fastest AC and solar charging speed that allows you to quickly charge from 0%-80% in an hour, always providing you the power ready-to-go!



Make Your Power Smarter

Make your power life a lot easier and smarter with APP. INFINITY 1500 supports remote monitoring, control and upgrade with smartphone application.



• Remote Power ON / OFF

- Advanced Settings
- Firmware Upgrade



Mobile Devices (10W)



(60W)





Home & Emergency Backup

For professionals and emergency preppers



Floor Lamp Wifi Router (300W) (25W)

TV Refrigerator (200W) (150W)

Blender (300W)





Laptop

(50W)

CPAP (65W)



Camera (5W)



Projector (300W)



Bluetooth Speaker (20W)

Electric Grill (1200W)



Light Bulb (30W)



Hair Dryer (2000W)









Electric Mower (1500W)



Circular Saw (1500W)

Microwave Oven (1300W)

Electric Stove (1200W)

Air Conditioner (1000W)